

SPECIFIC RADIO TUNE-UPS (Cont'd):

SEARS 934.38080700

TX. ADJ.: Peak - T-11, T-12, T-13, T-14, T-15  
RT301- RF Mtr. Adj.  
Pull: D-7, Q-10  
RX. ADJ.: RT-1 - Distorted Mixer Gain  
RT-2 - S Mtr. Adj.

TENNA 11302 (AM-FM-CB)

TX. ADJ.: Peak: L-602, L-603, L-604, L-605, L-607, L-609, L-610  
Pull: D-703, AMC Defeat  
RX. ADJ.: RV501- Sq. Rng.

TRS CHALLENGER 600

CHANGES: Remove driver and final carefully! Put final in driver position, put 2SC1307 in final slot. Pull D-2 or D202 out of circuit (may be marked either way).

NOTE: For frequency modification, see Secret CB, Vol. 7, pg. 23,24  
Identical through steps 1, 2, 3.

Step 4: Adjust T-603 and/or T-604 for output on all chan.  
Step 5: When finished with above, peak out at mid-range of band.

TX. ADJ.: Max.: T-214, L-208, CV-101  
VR210- RF Pwr. Adj. (Don not exceed 10 W dead key!)  
VR-1 - AMC  
VR-4 - Power Meter (Adj. to the red at dead key)  
RX. ADJ.: VR-2 - AGC  
VR-5 - Sq. Rng.  
VR-3 - RX. S Mtr.

VECTOR 770

TX. ADJ.: Peak: L-17, L-18, L-19, L-20, L-21, L-22, L-25, L-26  
FVR3 - AMC (Defeat, C-35)  
FVR4 - RF Mtr. Adj.  
RX. ADJ.: FVR1 - Sq. Rng.  
FVR2 - S Mtr. Adj.

VECTOR 790

TX. ADJ.: Peak: L-17, L-18, L-19, L-20, L-21, L-22, L-25, L-26  
FVR4 - RF Mtr. Adj.  
FVR3 - AMC (Defeat, pull both Q18 and FVR3)  
FVR5 - Voltage reg., set for 12.6 VDC.  
RX. ADJ.: FVR1 - Sq. Rng.  
FVR2 - S Mtr. Adj.