

This Manual is provided by
CBTricks.com

Someone who wanted to help you repair your equipment
scanned this manual.

If you would like to help us put more manuals online support us.

Supporters of CBTricks.com paid for the hosting so you would have this file.

CBTricks.com is a non-commercial personal website was created to help promote the exchange of service, modification, technically oriented information, and historical information aimed at the Citizens Band, GMRS (CB "A" Band), MURS, Amateur Radios and RF Amps.

CBTricks.com is not sponsored by or connected to any Retailer, Radio, Antenna Manufacturer or Amp Manufacturer, or affiliated with any site links shown in the links database. The use of product or company names on my web site is not endorsement of that product or company.

If your company would like to provide technical information to be featured on this site I will put up on the site as long as I can do it in a non-commercial way.

The site is supported with donation from users, friends and selling of the Galaxy Service Manual CD to cover some of the costs of having this website on the Internet instead of relying on banner ads, pop-up ads, commercial links, etc. to pay my costs. Thus I do not accept advertising banners or pop-up/pop-under advertising or other marketing/sales links or gimmicks on my website.

ALL the money from donations is used for CBTricks.com I didn't do all the work to make money (I have a day job). This work was not done for someone else to make money also, for example the ebay CD sellers.

All Trademarks, Logos, and Brand Names are the property of their respective owners.
This information is not provided by, or affiliated in any way with any radio or antenna Manufacturers.
Thank you for any support you can give.

CHASSIS COMPONENTS (TX)

<u>Schematic Symbol No.</u>	<u>Description</u>	<u>Part No.</u>	<u>Schematic Symbol No.</u>	<u>Description</u>	<u>Part No.</u>
<u>RESISTORS</u>			<u>CAPACITORS (continued)</u>		
R901	47 1/2W 5% Carbon	1-0738	C617	NOT USED	
R902	47 5%	1-0738	C618		
R601	A8048 10K Pot.	11-0095	C619		
R602	E595 - 5K Pot.	11-0010	C620		
R603	A657 25K Pot.	11-0008	C621		
R604	A657	11-0008	C622		
R605	15K 1/2W 5% Carbon	1-0768	C623		
R606	10K 10W 10% WW	1-0978	C624		
R607	3100 10W10% WW	1-1006	C625	220 MFD 25W	2-0391
R608	8500 10W 10% WW	1-0984	C626	.1 MFD 100V	2-0454
R609	220 1/2W 5% Carbon	1-0746	C627	.01 +80-20% Z5U 1KV	2-0100
R610	470	1-0750			
R611	470	1-0750			
R612	10	1-0180	L601	<u>INDUCTORS</u> 20Hy Choke C1515	3-0007
R613	1000 ohm 1/2W 5% Carbon	1-0754	L602	AIR-DUC 9 Turns	3-0017
			L603	.33 UHy Choke	3-0006
			L604	Ferrite Bead	3-0001
			L605	Ferrite Bead	3-0001
<u>CAPACITORS</u>					
C901	.01 +80-20%Z5U 500V	2-0049			
C902	.01	2-0049			
C601	10 -10 450V Electro.	2-0384			
C602	2.7-26 pF Variable	2-0423	T601	<u>TRANSFORMER</u> Modulation Transformer	4-0020
C603	250 PF 5% Dipped Mica	2-0297			
C604	.001 +80-20% g5U 500V	2-0036			
C605	68PF 5% Dipped Mica	2-0296			
C606	.01 +80-20% Z5U 1KV	2-0100			
C607	.01	2-0100			
C608	.001 +80-20% Z5U 500V.	2-0036			
C609		2-0036			
C610		2-0036			
C611	.01 +80-20% ZSU 1KV	2-0100			
C612	25 MFD25V Electro,	2-0370			
C613	2300 pF Feed-Through	2-0592			
C614	.01 MF 250VMyar	2-0458			
C615	.01 MF 250V	2-0458			
C616	.01 MF 250V	2-0458			
				<u>SHEET METAL</u> C-9015 Bottom Plate	5-0009
				D-9006:Dust Cover	5-0043
				A-9002 Meter Tab	5-0011
				Front Panel-Not Screened	5-9092
				Front Panel Overlay	13-0037
				D-9000 Chassis	5-0039
				C-9013 Synth. Bottom Cover	5-0094
				A-9008 Tuning Controls Cover	5-0045

CHASSIS COMPONENTS (TX)

<u>Schematic Symbol No.</u>	<u>Description</u>	<u>Part No.</u>	<u>Schematic Symbol No.</u>	<u>Description</u>	<u>Part No</u>
<u>KNOBS</u>			<u>MISCELLANEOUS</u>		
	Large K1251G Knob	6-0001	J601	Female Mic. Conn.	9-0038
	Small K900G Knob	6-0002	J602	SO239 Coax Conn.	9-0001
<u>DIODES</u>			P601	Cable Assy.	9-0072
CR901	1N541	7-0005	P602	Control Cable Plug	9-0069
CR902	1N541	7-0005	P603	Male Mic. Conn.	9-0037
D601	1N4005	7-0004		Lamp Socket	9-0011
D602	1N4005	7-0004		On-the-Air Lamp Holder	13-0014
CR601	1N3011B Zener	7-0007		A8003 Readout Window	13-0038
<u>PILOT LAMPS</u>				A8012 Enunciator	13-0016
				E593 RF Pick Up BD.	14-0001
1601	1847 Lamp	8-0022		Turner Microphone	14-0022
1602	CM-2181 Lamp	8-0026	M601	C594 Meter	15-0001
1603	CM-2181 Lamp	8-0026		Meter and Enunciator Bezel	15-0012
1604	CM-2181 Lamp	8-0026			
1605	CM-2181 Lamp	8-0026		<u>P.C. BOARD</u>	
1606	CM-2181 Lamp	8-0026		A10013 P.C. Board	14-0053
1607	CM-2181 Lamp	8-0026			
<u>SWITCHES</u>					
SW601	Spot Switch	11-0006			
SW602	LED Test Switch	11-0094			
SW603	E591 Mode Switch	11-0002			
SW604	E592 Meter Switch	11-0003			
SW605	Spring-Loaded Switch	11-0093			
<u>RELAY & SOCKET</u>					
K601	4 PDT Relay	10-0011			
	Relay Socket	10-0012			
	Relay Holddown Clip	10-0039			

FILTER P.C. BOARD (TX)

<u>Schematic Symbol No.</u>	<u>Description</u>	<u>Part No.</u>	<u>Schematic Symbol No.</u>	<u>Description</u>	<u>Part No.</u>
RESISTORS			CAPACITORS		
R201	220K 1/2W 5% Carbon	1-0782	C208	27 PF NPO. 5% 500V	2-0255
R202	3300	1-0760	C209	.04 +60-20% Z5U S00V	2-0051
R203	150 ohm	1-0744	C210	.01	2-0049
R204	250 ohm P.C. Pot	11-0091	C211	.01	2-0049
R205	470 ohm 1/2W 5% Carbon	1-0750	C212	68PF 10% Z5U 500V	2-0117
R206	470 ohm	1-0750	C213	.001 +80-20% 500V	2-0036
R207	22K	1-0770	C214	.001	2-0036
R208	68 ohm	1-0740	C215	.001	2-0036
R209	47K 2W 10% Carbon	1-0928	C216	.47 250V Mylar	2-0466
R210	1 SOO 1/2W 5% Carbon	1-0756	C217	.005 80-20% S00V	2-0048
R211	47K	1-0774	C218	100PF 10% Z5U 500V	2-0120
R212	2.2 Meg.	1-0794	C219	120 PF	2-0121
R213	470K	1-0786	C220	.22 2SOV Mylar	2-0457
R214	470K	1-0786	C221	25 MFD 25V Electro	2-0370
R215	3300	1-0760	C222	.01 +80-20% 500V	2-0049
R216	680 ohm	1-0752	C223	.001	2-0036
R217	100K	1-0778	C224	20 PF NPO - for Filtech	2-0262
R218	1000	1-0754		Filters Only	
R219	500K P.C. Pot	11-0027	C225		2-0262
R220	1500 1/2W 5% Carbon	1-0756	C226		2-0262
R221	4700	1-0762	C227		2-0262
R222	33K 1W 10% Carbon	1-0849			
R223	470K 1/2W 5% Carbon	1-0786		DIODES	
R224	150 ohm 1W 10% Carbon	1-0821	D201	1 N4005	7-0004
R225	22 ohm 1/2W 5% Carbon	1-0734			
R226	1500	1-0756		TUBES	
R227	15K 2W 10% Carbon	1-0922	V201	12AX7	8-0011
R228	15K 1/2W 5% Carbon	1-0768	V202	65A6	8-0004
R229	3300	1-0760	V203	12AX7	8-0011
			V204	12AU7	8-0010
			V205	6BQ5	8-0008
CAPACITORS					
C201	8- 50PF Variable	2-0430			
C202	150 PF 10% Z5U	2-0122		SOCKETS	
C203	.005 +80-20% Z5U 500V	2-0048		7 Pin P.C. Tube Socket	9-0023
C204	270 PF 20% Disc 500V	2-0025		9 Pin	9-0024
C205	5-25PF Variable	2-0429			
C206	.005 +80-20% Z5U 500V	2-0048		P.C. BOARD	
C207	1.1 PF Tubular	2-0460		B-10005 P.C. Board	14-0015

FILTER P.C. BOARD (TX)

Schematic Symbol No.	DESCRIPTION	Part No.	Schematic Symbol No.	DESCRIPTION	Part No.
<u>CRYSTALS - FILTERS</u>					
CR201	5.645 Crystal	16-0002			
FL201	5.6465 USB Filter	16-0001			
FL202	5.6435 LSB Filter	16-0018			
<u>TRASFORMERS</u>					
T201	B8542 Bal. Modulator	4-0018			
T202	B8529 5 MHz XMFR	4-0017			

DRIVER-FINAL P.C. BOARD (TX)

Schematic Symbol No	DESCRIPTION	Part No.	Symbol No.	Schematic DESCRIPTION	Part No.
	<u>RESISTORS</u>			<u>CAPACITORS</u>	
R301	NOT USED		C301	.001 +80-20% Z5U 500V	2-0036
R302	1000 1/2 W 5% Carbon	1-0754	C302	.001	2-0036
R303	470	1-0750	C303	.001	2-0036
R304	68K	1-0776	C304	.01	2-0049
R305	4700	1-0762	C305	.001	2-0036
R306	10K	1-0766	C306	.001	2-0036
R307	22 ohm	1-0734	C307	30 PF NPO 10% 500V	2-0265
R308	150 ohm 1/2W 5%"	1-0744	C308	2.2 PF Tubular	2-0462
R309	150K 1/2W 5%	1-0780	C309	220 PF 20% Z5U 500V	2-0023
R310	22K	1-0770	C310	2.2 PF NPO .25 PF 1KV	2-0268
R311	100	1-0742	C311	.01 +80-20% Z5U 500V	2-0049
R312	680	1-0752	C312	270PF 20% Z5U 500V	2-0025
R313	10K	1-0766	C313	5.0 PF NPO	2-0001
R314	10 ohm	1-0180	C314	.001 +80-20% Z5U 500V	2-0036
R315	820	1-0226	C315	.04	2-0051
R316	1500 5W 10% WW	1-0964	C316	.001	2-0036
R317	680K 1/2W 5% Carbon	1-0788	C317	.01	2-0049
R318	25K P.C. Pot.	11-0026	C318	25 MFD 50V Electro.	2-0373
R319	150K 1/2W 5% Carbon	1-0780	C319	.001 +80-20% Z5U 500V	2-0036
R320	470K	1-0786	C320	1000 MFD 16V Electro.	2-0390
R321	22K	1-0770	C321	.04 +80-20% Z5U 500V	2-0051
R322	1000	1-0754	C322	.04	2-0051
R323	10K	1-0766	C323	.04	2-0051
R324	3300	1-0760	C324	2 MFD 150V Electro.	2-0595
R325	47K	1-0774	C325	1 MFD 50V Electro.	2-0371
R326	100	1-0742			
R327	1M	1-0790			
R328	100	1-0742			
R329	150	1-0744			

DRIVER-FINAL P.C.BOARD (TX)

Schematic Symbol No.	DESCRIPTION	Part No.	Schematic Symbol No.	DESCRIPTION	Part No.
<u>INDUCTORS-TRANSFORMERS</u>			<u>SOCKETS</u>		
L301	5.6 UHy Choke	3-0003		7 Pin P.C. Tube Socket	9-0023
L302	18 UHy	3-0005		9 Pin P.C.	9-0024
L303	18 UHy	3-0022			
L304	Ferrite Bead	3-0001		<u>P.C. BOARD</u>	
L305	Ferrite Bead	3-0001		B-10006 P.C. Board	14-0016
L604	2.2 MHy Choke	3-0013			
T301	B8546 27 MHz Transformer	4-0019			
T302	B8546 27 MHz Transformer	4-0019			
T303	B8546 27 MHz Transformer	4-0019			
<u>DIODES</u>					
D301	1N4005	7-0004			
D302	NOT USED				
D303	1N914 or 1N4148	7-0013			
D304	1N914 or 1N4148	7-0013			
<u>TRANSISTORS</u>					
Q301	2N5086	7-0014			
Q302	2N5086	7-0014			
Q303	2N5209	7-0015			
Q304	40327	7-0030			
<u>TUBES</u>					
V301	6CB6	8-0016			
V302	12BY7	8-0015			
V303	7558	8-0014			

SYNTHESIZER P.C. BOARD (TX)

Schematic Symbol No.	Description	Part No.	Schematic Symbol No.	Description	Part No.
	<u>RESISTORS</u>			<u>RESISTORS</u>	
R701	47K ohm 1/4W	1-0690	R735	1K ohm 1/4W	1-0670
R702	150	1-0660	R736	1K ohm	1-0670
R703	1 Meg ohm	1-0662	R737	220 ohm	1-0661
R704	1K ohm	1-0670	R738	47K 1/4W	1-0690
R705	220K ohm	1-0698	R739	47K 1/4W	1-0690
R706	6.8K ohm	1-0680	R740	47K 1/4W	1-0690
R707	2.2K ohm	1-0674	R741	47K 1/4W	1-0690
R708	330K ohm	1-0700		<u>CAPACITORS</u>	
R709	6.8K ohm	1-0680	C701	.01 Mylar	2-0552
R710	1.5K ohm	1-0672	C702	160pF 5% Dip Mica	2-0294
R711	680 ohm	1-0668	C703	10 pF NPO 10% 500V	2-0259
R712	3.3K ohm	1-0676	C704	50 pF N750 10%500V	2-0253
R713	680 ohm	1-0668	C705	8-50 pF	2-0430
R714	470 ohm	1-0666	C706	180 pF	2-0598
R715	47K ohm	1-0690	C707	120pF Z5U 10% 500V	2-0121
R716	2.2K ohm	1-0674	C708	.1 Mylar	2-0551
R717	1K ohm	1-0670	C709	.01 Mylar	2-0552
R718	1K ohm	1-0670	C710	10 pF NPO 10% 500V	2-0259
R719	2.2K ohm	1-0674	C711	30pF NPO 10% 500V	2-0112
R720	100K ohm	1-0694	C712	3.3 MFD 16V	2-0560
R721	2,2K ohm	1-0674	C713	.1 Mylar	2-0551
R722	47K ohm	1-0690	C714	100 pF N750	2-0599
R723	150 ohm	1-0660	C715	.001 Z5U 500V	2-0036
R724	47 ohm	1-0654	C716	.001 Z5U 500V	2-0036
R725	270 ohm	1-0663	C717	10 MFD 16V	2-0561
R726	3.9K ohm	1-0677	C718	330 pF 10% NPO	2-0601
R727	6.8K ohm	1-0680	C719	120pF N220 1Ky 5%	2-0600
R728	100 ohm	1-0658	C720	.001 Z5U 500V	2-0036
R729	47 ohm	1-0654	C721	180 pF SL S0V	2-0547
R730	68K ohm	1-0692	C722	.1 Mylar	2-0551
R731	10K ohm	1-0682	C723	.01 Mylar	2-0552
R732	68K ohm	1-0692	C724	.001 Z5U 500V	2-0036
R733	1.0K ohm	1-0682	C725	10 pF NPO 10% 500V	2-0259
R734	10K ohm	1-0682	C726	330 pF NPO 10% 100V	2-0601

SYNTHESIZER P.C. BOARD (TX)

Schematic Symbol No.	Description	Part No.	Schematic Symbol No.	Description	Part No.
<u>CAPACITORS</u>			<u>DIODES</u>		
C727	10 pF NPO 10% 500V	2-0259	D701	MV2111 Varactor	7-0034
C728	.001 Z5U 500V	2-0036	D702	1N914 or 1N4148	7-0013
C729	.1 Mylar	2-0551			
C730	.01 Mylar	2-0552	<u>TRANSISTORS</u>		
C731	.1 Mylar	2-0551	Q701	MPS6514	7-0032
C732	25 MFD 25V	2-0370	Q702		7-0032
C733	.1 Mylar	2-0551	Q703		7-0032
C734	.01 Mylar	2-0552	Q704		7-0032
C735	.1 Mylar	2-0551	Q705		7-0032
C736	30 pF NPO 10% 500V	2-0112	Q706		7-0032
C737	68 pF Z5U 10% 500V	2-0117	Q707		7-0032
C738	68 pF Z5U 10% 500V	2-0117	Q708		7-0032
C739	.001 Z5U 500V	2-0036	Q709		7-0032
C740	5 MFD 50V	2-0372	Q710		7-0032
C741	.001 Z5U 500V	2-0036	Q711		7-0032
C742		2-0036	Q712		7-0032
C743		2-0036	Q713		7-0032
C744		2-0036			
C745		2-0036	<u>INTEGRATED CIRCUITS</u>		
C746		2-0036	IC701	MC145116	7-0126
C747		2-0036	IC702	CD4008A	7-0123
C748		2-0036	IC703	7808 or LM340-8	7-0128
C749		2-0036			
C750		2-0036	<u>SOCKETS</u>		
C751		2-0036		16 Pin I.C. Socket	9-0027
				18 Pin I.C. Socket	9-0070
<u>INDUCTORS</u>			<u>P.C. BOARD</u>		
L701	.33 uH Coil with Shield	3-0067			
L702	.33 uH	3-0067			B-10015 P.C. Board 14-0073
L703	Not Used				
L704	5.6 uH Choke	3-0003			
L705	.6 uH Coil with Shield	3-0068	CR701	10.24 MHz 16-0162	
L706	2.2 mH Choke	3-0013			
L707	1 uH Choke	3-0020			
L708	1 uH	3-0020			
L709		3-0020			

CHASSIS COMPONENTS RX

Schematic Symbol No.	Description	Part No.	Schematic Symbol No.	Description	Part No.
<u>PILOT LAMPS</u>					
I1	1847 Lamp	8-0022			
I2	1847 "	8-0022			
<u>SWITCHES</u>					
SW1	A8017 Switch	11-0032			
SW2	A8018 Switch	11-0031			
<u>MISCELLANEOUS</u>					
	SO239 Coax Conn.	9-0001			
	Pilot Lamp Socket	9-0011			
J1	Speaker Jack	9-0033			
J2	Control Cable Socket	9-0061			
F1	3 Amp Fuse Slow Blow	10-0038			
F2	Fuse 3A Wire Leads	10-0043			
XF1	Fuse Holder	10-0002			
	6' Line Cord	10-0004			
	Dial	13-0023			
	Speaker	14-0010			
M1	Meter	15-0003			
	Meter Bezel	15-0012			
	T-Clips for Ennunc. Window	6-0076			
L1	Ferrite Bead A361	3-0001			
L2		3-0001			
L3		3-0001			
L4		3-0001			

FRONT END P.C. BOARD RX (continued)

Schematic			Schematic		
Symbol No.	Description	Part No.	Symbol No.	Description	Part No.
<u>TRANSFORMERS</u>					
T101	B8546 27 MHz	4-0019			
T102	B8141 4 MHz	4-0022			
	Coil Shields	5-0078			
<u>DIODES</u>					
D101	1N4148 or 1N914	7-0013			
<u>TUBES</u>					
VI01	6DS4	8-0003			
V102	6DS4	8-0003			
V103	12AT7	8-0009			
V104	12AT7	8-0009			
<u>SOCKETS</u>					
	9 Pin P.C. Tube Socket	9-0024			
	Crystal Socket	9-0039			
	Nuvistor P.C. Socket	9-0032			
<u>P. C. BOARD</u>					
	P. C. Board	14-0020			

IF P.C. BOARD RX

Schematic Symbol No.	Description	Part No.	Schematic Symbol No.	Description	Part No.
<u>RESISTORS</u>			<u>RESISTORS (cont'd)</u>		
R201	100K 1/2W 5% Carbon	1-0778	R235	100K 1W 10% Carbon	1-0855
R202	680	1-0752	R236	1.8K	1-0757
R203	47K	1-0774	R237	100K 1/2W 5% Carbon	1-0778
R204	2200	1-0758	R238	2.2K 1/2W 5% Carbon	1-0758
R205	100K	1-0778	R239	470K ohm 1/2W 5% Carbon	1-0786
R206	680	1-0752	R240	270 ohm 1W 10% Carbon	1-0824
R207	47K	1-0774	R241	10 Meg. 112W 5% Carbon	1-0802
R208	2200	1-0758	R242	10 Meg. 1/2W 5% Carbon	1-0802
R209	100K	1-0778			
R210	1000	1-0754			
R211	47K	1-0774	<u>CAPACITORS</u>		
R212	2200	1-0758	C201	39 PF NPO 500V	2-0266
R213	3300	1-0760	C202	.01 +80-20% Z5U 500V	2-0049
R214	220K	1-0782	C203	.01	2-0049
R216	470K	1-0786	C205	.01	2-0049
R217	470K	1-0786	C206	.01 1KV	2-0100
R218	1MEG.	1-0790	C207	.01 500V	2-0049
R220	470K	1-0786	C209	.1 MFD 250V Mylar	2-0459
R221	22K	1-0770	C210	.01 +80-20% Z5U 500V	2-0049
R222	100 ohm	1-0742	C211	.01 1KV	2-0100
R223	47K	1-0774	C212	.01 500V	2-0049
R224	270K	1-0783	C213	.01	2-0049
R225	15K 2W 10% Carbon	1-0922	C214	.01	2-0049
R226	4700 1/2W 5% Carbon	1-0762	C215	.011KV	2-0100
R227	150 ohm	1-0744	C216	100 PF 10% Mica	2-0292
R228	100K 1/2W	1-0778	C217	100 PF	2-0292
R229	4.7 Meg.	1-0798	C218	.01 +80-20%Z5U 500V	2-0049
R230	470K 1/2W	1-0786	C219	270PF 10% 500V	2-0025
R231	1Meg.	1-0790	C220	.02 +80 -.20%Z5U 500V	2-0050
R232	330K 1/2W	1-0784	C221	.01	2-0049
R233	10 Meg.	1-0802	C222	.01	2-0049
R234	10K 1/2W	1-0766	C223	3-12 PF Variable	2-0431

IF P.C. BOARD RX (continued)

<u>Schematic</u>			<u>Schematic</u>		
<u>Symbol No.</u>	<u>Description</u>	<u>Part No.</u>	<u>Symbol No.</u>	<u>Description</u>	<u>Part No.</u>
<u>CAPACITORS (cont'd)</u>			<u>DIODES</u>		
C224	3-12 PF Variable.	2-0431	D201	1N4005	7-0004
C225	68 PF Dipped Mica	2-0296	D202	1N914 or 1N4148	7-0013
C226	330 PF Disc.	2-0027	D203	1N4005	7-0004
C227	270 PF Mica, 5%	2-0295	D204	1N91-4or 1N4148	7-0013
C228	.01 +80-20%. Z5U 500V	2-0049	D205	PD155	7-0008
C229	.002	2-0040			
C230	430 PF 5% Mica	2-0335		<u>TUBES</u>	
C231	.002 +80 -20% Z5U 500V	2-0040	V201	6BA6	8-0004
C232	.22 MFD 250V Mylar	2-0457	V202	6BA6	8-0004
C233	1.SpF Tubular	2-0461	V203	6BA6	8-0004
C234	.01 +80-20% Z5U 500V	2-0049	V204	6BE6	8-0005
C235	.001	2-0036	V205	12AX7	8-0011
C236	.1 MFD 250V Mylar	2-0459	V206	6AQ5	8-0007
C237	8 MFD 150V Electro.	2-0403			
C238	.001 +80-20% Z5U 500V	2-0036		<u>SOCKETS</u>	
C239	5 MFD 50V, Electro.	2-0372		7 Pin P.C. Tube Socket	9-0023
C240	.01 +80-20%, Z5U 1KV	2-0100		9 Pin	9-0024
C241	470pF Z5U 10% 500V.	2-0132			
C242	470 pF Z5U	2-0132			
C243	2 MFD 450V Electro.	2-0395		<u>P.C. BOARD</u>	
C18	470-pF Z5U 500V	2-0132		P, C, Board	14-0021
C21	470. pF.Z5U 500V	2-0132			
<u>INDUCTORS</u>					
L201	2.2 MHy Choke	3-0013			
L202	2.2 MHy	3-0013			
<u>TRANSFORMERS</u>					
T201	B8584 455 KHz	4-0023			
T202	B8584	4-0023			
T203	B8584	4-0023			
T204	B8584	4-0023			
T205	B8584	4-0023			

CRYSTAL SWITCHING BOARD RX

<u>Schematic</u>			<u>Schematic</u>		
<u>Symbol No.</u>	<u>Description</u>	<u>Part No.</u>	<u>Symbol No.</u>	<u>Description</u>	<u>Part No.</u>
<u>RESISTORS</u>					
R501	15K ohm 1/4W C.F.	1-0684			
R502	1 K	1-0670			
R503	15K	1-0684			
R504	1K	1-0670			
<u>CAPACITORS</u>					
C501	.001 Z5U +80-20% 500V	2-0036			
C502	.001	2-0036			
<u>TRANSISTORS</u>					
Q501	MPS-6514	7-0032			
Q502	MPS-6514	7-0032			
<u>CRYSTALS</u>					
CR501	22.82 MHz Crystal	16-0163			
CR502	23.14 MHz Crystal	16-0164			
<u>P. C. BOARD</u>					
	AI0014 P.C. Board	14-0069			

LED P.C. BOARD RX

<u>Schematic</u>			<u>Schematic</u>		
<u>Symbol No.</u>	<u>Description</u>	<u>Part No.</u>	<u>Symbol No.</u>	<u>Description</u>	<u>Part No.</u>
<u>RESISTORS</u>					
R401	390 ohm 1/2W 5% Carbon	1-0749			
R402	390 ohm	1-0749			
<u>LED'S</u>					
1401	MV-5054-1	8-0027			
1402	MV-5054-1	8-0027			
1403	MV-5054-1	8-0027			
1404	MV-5054-1	8-0027			
1405	MV-5054-1	8-0027			
1406	MV-5054-1	8-0027			
<u>P. C. BOARD</u>					
	P. C. Board	14-0023			
	LED Bracket	6-0275			
<u>CAPACITORS</u>					
C401	470pF Z5U 10% 500V	2-0132			