

## Specific Radio Tune-ups

BOMAN CB 555

VR 481: Adjust for 100% modulation  
VR 491: RF meter adjustment  
Adjust L451 and L464 for maximum RF power  
VR 151: S meter adjustment

BOMAN CBH 900

Adjust L7, L11, L12 for maximum RF power  
RV1a: Adjust to obtain 13.8 volts power  
RV2 : Adjust for 100% modulation  
RV3 : S meter adjustment  
RV4 : RF meter adjustment  
Connect pins 9 and 10 of IC1 together for  
more frequencies.

BOMAN CB 910

Adjust L7, L11, and L12 for maximum RF power  
RV2: Adjust for 100% modulation  
RV4: RF meter adjustment **SEE MASTER COPY B & C.**

Connect pin 9 to pin 7 of IC1 for more frequencies  
(channels 10-40) or connect pins 9 and 10 together  
for more frequencies.

BOMAN CB930

Adjust L7, L11, and L12 for maximum RF power  
RV2: Adjust for 100% modulation  
RV4: RF meter adjustment  
RV3: S meter adjustment  
**SEE MASTER COPY B & C**

BOMAN CBR 9940

VR 903: Adjust for 100% modulation  
VR 902: Adjust in addition to VR 903  
for maximum modulation  
VR 901: Adjust for maximum power