

KRACO KCB4020

Adjust L7, L11, and L12 for maximum AM power

RV2: Adjust for 100% modulation

RV3: S meter adjustment

RV4: RF panel meter adjustment

\* See conversion for Bowman CB930 for more frequencies

JOHNSON VIKING 260/270

Adjust L84 for maximum RF power

Adjust R49 for 100% modulation +T84 +T85

for cleanest RF envelope

Connect pins 13 and 14 of U131 together for more frequencies

MIDLAND 79-892

ADJUST VR4 for maximum AM power

RV12: Adjust for 100% modulation

RV3: RF power meter adjustment

RV2 : SSB power adjustment

Adjust T6, L7, L11, and L13 for maximum RF output of USB

MIDLAND76-858

Adjust L7, L11, and L12 for maximum RF power

RV2: Adjust for 100% modulation

RV4: Adjustment for RF power meter

RV3; S meter adjustment

\* See conversion for Boman CB930 for high frequencies

PIERCE SIMPSON LEOPARD B

VR901: Adjust for maximum RF power

VR903: Adjust for 100% modulation

VR902: Also adjust for modulation

MOPAR 4094177

Adjust L7, L11, and L12 for maximum RF power output

RV4: TX meter adjustment

RV3: S meter adjustment

Connect pins 9 and 10 of IC1 together for more frequencies