

UTAC TRX-500

Adjust L15, and L17 for maximum RF power output
Adjust VR7 for 100% modulation
VR8: RF panel meter adjustment
Take pin 10 of IC501 high (4.30V) for more frequencies

ROYCE 604

Adjust VR202 or clip D202 for 100% modulation
Adjust T302 and L303 for maximum power

ROYCE 619

For AM modulation cut out diode 202 located under meter lamp.

ROYCE 1-625

Adjust VR1602 for maximum modulation
Connect pin 6 of PLL to 5.93 volt source;
Connect pin 5 of PLL to 5.93 volt source;
Connect pin 7 of PLL to 5.93 volt source:
For adding more frequencies

ROBYN DG130D

Adjust L13, L12, L11, L10 for maximum power
Adjust VR6 for 100% modulation
VR4: RF power meter adjustment

ROBYN T-240D

Adjust VR4 for 100% modulation
Adjust L801, VC901, VC902, and L702(top)
for maximum power
VR6: RF panel meter adjustment

ROBYN WV110

Adjust L15, L13, L12, L11, and L10 for maximum power
Adjust VR6 for 100% modulation
VR4: RF power meter adjustment