

SPECIFIC RADIO TUNE-UPS (Cont'd):

CRAIG L231 (AM/SSB)

RX: R309 - AGC
R315 - Squelch range
R229 - AM S meter adjust
R240 - SSB S meter adjust
TX: Peak - T103, T102, T101, L111, L109, L106
NOTE: Do not touch (C101A, C101B, L114)
R414, R401 - Carrier balance
R130 - SSB ALC
R605 - AM AMC
R106 - RF meter (AM) adjust
R711 - Dimmer adjust for display
NOTE: This unit has a 20W final so don't defeat AMC & ALC.

DAK MARK II

NOTE: No SAMS available for this radio - use SAMS 190 and refer to ALARON B-4075.

RX: RV101 - Squelch range
RV102 - S meter adjust
TX: Peak: L302, L303, L304, L305, L306, L307, L308, L309 (Do not touch L312 - TVI).
RV219 - Mic gain
RV301 - RF meter adjust
NOTE: If you have trouble getting modulation up, pull C226. SAMS 190 shows C226 as a 33mf diode? (O.E.M. must be broke!) If unit has MPS-u31 final - don't push it!

DELCO 90BFTC1 & 90BCB1 (AM,FM,CB)

RX: RV1 - Squelch range
TX: Peak: T3, L4, L8, L9
RV2 - AMC (defeat, remove RV2)
Unit has a 12W final.

FORMAC 40

(Odd ball company) for service info see: SAMS 166 - refer to Lafayette HB-740.

RX: RV1 - Squelch range
RV3 - S Meter adjust
TX: Peak: L7, L11, L12
RV2 - AMC (defeat is C96)
RV4 - RF meter adjust
Unit has a 12W final.