

SPECIFIC RADIO TUNE-UPS (Cont'd):

Lafayette Model LM-300:

PLL02A Chip-see Volume 3 for frequency modification.

RX: L3; VCO Coil.
RV2; Modulation Adjust, clip D13 or remove Q17.

TX: Adjust T18, T7, T8 and L7, L11, L12.
RV4; RF Power Meter.
RV5; Alert tone level.

Lake 410 MM55108N:

RX: RV201 Squelch Range.
RV101 S Meter.

TX: Adjust L301, L302, L303, L304, L305, L301 for max.
RV202; AMC or remove Q203.
RV301; RF Power Meter.

Lake 450 MM55126N:

RX: VR302; Sq. Range.
VR402; S Meter

TX: Adjust PLL5, PLL6, TX1 for max.
VR301; AMC
RV201 RF Pwr. Meter.
PLL1 VCO coil.

Lake 600 MC14506P:

RX: VR1; Squelch Range.
VR3; S Meter.

TX: Peak PLL5, PLL6, TX1, LC202, LC203 and LC204.
VR2; AMC or remove Q15.
VR4; RF Power Meter.
PLL1; VCO coil.

Midland 3001 (77-003) LC 7130:

RX: RV101; Squelch Range.
RV103; S Meter.

TX: Peak L301, L302, L303, L304, L305, L306.
RV201; AMC
RV202; RF Power Meter.