

SPECIFIC RADIO TUNE-UPS (Cont'd):

Midland 77-824C LC7120:

RX: RV101; Squelch Range.
RV103; S Meter.

TX: Peak L301, L302, L303, L304, L305 and L306.
RV201; AMC or clip D203.
RV202; RF Power Meter.
RV301; A.W.I.
L203; VCO Coil.

Midland 78-574 PLL02A:

RX: RV10; RF Gain Range.
RV6; SSB AGC.
RV7; AM SQ. Range.
RV8; SSB SQ. Range.
RV5; AM S Meter.
RV4; SSB S Meter.

TX: Adjust for Max. on USB; T204, T205, T3, T209, L209, L212,
214.
RV1, RV2; Carrier Balance.
RV206; Final Bias-adjust for .7V bias at base of Q208.
RV3; SSB Mod. Gain.
RV201; SSB ALC.
RV9; AM AMC or remove C71.
RV202; RF Meter.
VR1; AM Power.

Pace 8113 MM5107N:

RX: R135; Squelch Range.
R137; S Meter Zero.

TX: Peak L301, L302, T302 and L304, L307, L308.
R220; AMC.
R325; TX Power Meter.

Zapper can be used. Insert in place of C420.

C402; VCO Coil.