

BOWMAN CB-755 (23 CH. - XTAL RIG)

RX: R-31, Squelch Range
R-24, S Meter

TX: R-109, RF Meter

Peak T10,T11,T12,T13,T14,L3,L6,L7 (Pour It On!

Unit has 12W Driver & 25W Final!)

AMC Defeat---D-17

CHANNEL MASTER CB6834

RX:

Peak T304,T303 on 455KC.

Peak T302,T301,L102,L101 on Ch.19.

VR1 A G C

VR3 Squelch Range

VR4 S Meter

TX:

Peak L901,L903,L905.

F901 is T.V.I. Filter

VR6 is Modulation control (or remove Q503)

VR7 RF Power Meter

MIKE WIRING: 4 Pin Locking Ring Type.

1. REC. (Black)
2. Audio hot (Yellow)
3. Xmit (White)
4. Shield