

MIDLAND 13-879

RX: Peak IFT1, IFT2, on 455KC.
Peak L1, L2, L3, L4, on Ch.13.
VR3 Squelch Threshold
VR6 S Meter 100uV= S9

TX: Peak L7, L8, L9, L10, L11, L15.
VR5 RF Power Meter
VR7 Adjust for 13.8 VDC.
L16 T.V.I. filter

Extra channels are obtained in same manner as in 13-862 model previously described.

MIKE WIRING: 4 Pin Locking Ring Type

1. Audio hot (Red)
2. Ground (Shield & Blue)
3. Xmit (White)
4. REC (Black)

No protection diode on DC.

Wire in a HEPL70 (Item #99) as shown:

(Item #99 can be obtained from "Secret CB".)

