

## TRS CHALLENGER 460 (861)

### RX:

Peak T108, T107, T106 on 455KC.

Peak T105, T104, T103, T102, T101 on Ch.19.

VR2 AGC

VR8 IF Gain

VR6 Squelch Range

VR5 8 Meter S9=100uV.

### TX:

Peak T112, T114, L101, L103, L106, L107.

L109 is T.V.I. Filter

VR3 Modulation Control

VR4 RF Power Meter

### FREQUENCY

Switch X3 (36.750) Xtal to go higher or lower.

T3 is VCO Coil.

MIKE WIRING: 4 Pin Locking Ring Type. Electronic Switching

1. Audio hot (yellow)
2. Common (shield)
3. REC (violet)
4. Xmit (red)