

This Manual is provided by  
***CBTricks.com***

Someone who wanted to help you repair your equipment put together this information.

## Cobra 142GTL Parts List

If you would like to help us put more manuals online support us.

**If you would like to help with this project let us know.**

Supporters of CBTricks.com paid for the hosting so you would have this file.

CBTricks.com is a non-commercial personal website was created to help promote the exchange of service, modification, technically oriented information, and historical information aimed at the Citizens Band, GMRS (CB "A" Band), MURS, Amateur Radios and RF Amps.

CBTricks.com is not sponsored by or connected to any Retailer, Radio, Antenna Manufacturer or Amp Manufacturer, or affiliated with any site links shown in the links database. The use of product or company names on my web site is not endorsement of that product or company.

If your company would like to provide technical information to be featured on this site I will put up on the site as long as I can do it in a non-commercial way.

The site is supported with donation from users, friends and selling of the Galaxy Service Manual CD to cover some of the costs of having this website on the Internet instead of relying on banner ads, pop-up ads, commercial links, etc. Thus I do not accept advertising banners or pop-up/pop-under advertising or other marketing/sales links or gimmicks on my website.

ALL the money from donations is used for CBTricks.com I didn't do all the work to make money (I have a day job). This work was not done for someone else to make money also, for example the ebay CD sellers.

All Trademarks, Logos, and Brand Names are the property of their respective owners.

This information is not provided by, or affiliated in any way with any radio or antenna Manufacturers.

**Thank you for any support you can give.**

# BILL OF MATERIAL FOR COBRA 142GTL

CIRCUIT SYMBOL	DESCRIPTION	DYNASCAN PART NO.
<b>SEMICONDUCTORS</b>		
IC-1	Integrated Circuit, UHIC-007 .....	307-143-9-001
IC-2	Integrated Circuit, MB8719 .....	307-128-9-002
IC-3	Integrated Circuit, AN612 .....	307-143-9-002
IC-4	Integrated Circuit, TA7222P .....	307-143-9-003
IC-5	Integrated Circuit, MB3756 .....	307-133-9-005
IC-6	Integrated Circuit, SO42P .....	307-143-9-004
FET-1	Field Effect Transistor, 2SK19-BL .....	182-037-9-001
TR-7,14,30,31,45	Transistor, 2SA733-P .....	177-020-9-001
TR-36	Transistor, 2SC458-C .....	176-048-9-002
TR-4,5,8,11,13,15,20,27, 28,29,32,33,35,37,44, 301	Transistor, 2SC945A-Q .....	176-059-9-003
TR-39	Transistor, 2SC1306 .....	172-024-9-002
TR-34,302	Transistor, 2SC1419-C .....	176-055-9-004
TR-9,17,18	Transistor, 2SC1674-L .....	176-081-9-002
TR-1,2,6,10,12,19,21,22, 23,24,25,42	Transistor, 2SC1675-L .....	176-065-9-001
TR-3,16	Transistor, 2SC1730-L .....	176-073-9-001
TR-40	Transistor, 2SC496-O .....	176-087-9-001
TR-41	Transistor, 2SC1969-B .....	176-087-9-002
TR-38	Transistor, 2SC1973 .....	176-073-9-003
TR-401	Transistor, 2SD188-M .....	172-040-9-001
D-3,4,5,6,7,8,10,11,12,15, 16,17,18,19,20,23,24, 25,26,27,28,29,30,31, 32,33,34,35,36,38,39, 40,41,43,44,48,49,406	Diode, 1S1588 .....	151-051-9-001
D-1,2,9,21,22,42	Diode, 1N60 .....	150-001-9-005
D-51,52,53	Diode, 1N60P .....	150-006-7-001
D-13,14	Diode, MC301 .....	151-072-9-001
D-60,407	Diode, SR1K-2 .....	151-045-9-001
D-301	Diode, Zener, WZ-061 .....	152-052-9-002
D-302	Diode, Zener, BZ-162 .....	152-057-9-001
D-402	Diode, L.E.D., TLR103 .....	158-022-9-001
D-405	Diode, L.E.D., TLG103 .....	158-022-9-002
D-401	Diode, L.E.D., TLR321 .....	158-014-9-001
D-46	Diode, Varister, MV-1Y .....	004-175-9-001
D-47	Diode, Varister, MV-13YH .....	153-011-9-001
D-37	Diode, Varicap, 1S2687D .....	153-008-9-001
D-408	Diode, S5VB-10 .....	151-065-9-001
<b>INDUCTORS</b>		
L-1	Coil, LA-038 .....	060-018-9-001
L-27	Coil, LA-160 .....	060-025-9-008
L-2	Coil, LA-179 .....	060-025-9-010
L-14	Coil, LA-195 .....	060-030-9-001
L-13	Coil, LA-216 .....	060-030-9-002
L-19	Coil, LA-217 .....	060-030-9-003

**CIRCUIT  
SYMBOL**

**DESCRIPTION**

**DYNASCAN  
PART NO.**

**INDUCTORS (Continued)**

L-20	Coil,	LA-218 .....	060-030-9-004
L-26	Coil,	LA-219 .....	060-030-9-005
L-28	Coil,	LA-220 .....	060-030-9-006
L-17	Coil,	LA-223 .....	060-030-9-007
L-29	Coil,	LA-254 .....	060-030-9-008
L-3	Coil,	LA-255 .....	060-030-9-009
L-18	Coil,	LA-256 .....	060-030-9-010
L-6	Coil,	LA-257 .....	060-030-9-011
L-7	Coil,	LA-258 .....	060-030-9-012
L-8	Coil,	LA-259 .....	060-030-9-013
L-9	Coil,	LA-260 .....	060-030-9-014
L-10	Coil,	LA-261 .....	060-030-9-015
L-5	Coil,	LA-262 .....	060-030-9-016
L-4	Coil,	LA-263 .....	060-030-9-017
L-36,39	Coil,	LC-019 .....	041-088-9-001
L-401,402	Coil,	LD-013 .....	044-043-9-002
L-31,34	Coil,	LD-087 .....	044-048-9-003
L-30	Coil,	LD-096 .....	044-053-9-002
L-33,35	Coil,	LD-098 .....	044-053-9-003
L-32	Coil,	LD-101 .....	014-053-9-004
L-40	Coil,	LD-071 .....	044-043-9-006
L-50,51,52	Coil,	LD-077 .....	763-084-9-001
L-403	Coil,	LD-089 .....	044-048-9-002
L-37,38	Coil,	LE-051 .....	044-043-9-008
L-12,25	Micro Inductor,	LZ-012, 100 $\mu$ H .....	041-087-9-002
L-11,15,16,21,22,23,24	Micro Inductor,	LZ-012, 470 $\mu$ H .....	041-088-9-004
T-401	Power Transformer,	TF-143 .....	765-142-9-001

**SEMI-FIXED & VARIABLE RESISTORS**

VR-8	Resistor, Semi-Fixed,	RV-189 500 ohm B .....	008-342-9-001
VR-6,9	Resistor, Semi-Fixed,	RV-189 5K ohm B .....	008-316-9-004
VR-1,5,7	Resistor, Semi-Fixed,	RV-189 10K ohm B .....	008-342-9-002
VR-10,12	Resistor, Semi-Fixed,	RV-189 100K ohm B .....	008-316-9-001
RT-301	Resistor, Semi-Fixed,	RV-146 300 ohm B .....	008-346-9-001
VR-2	Resistor, Semi-Fixed,	RV-189 1K ohm B .....	008-334-9-001
VR-3	Resistor, Semi-Fixed,	RV-189 3K ohm B .....	008-323-9-001
VR-405	Resistor, Variable,	RV-036 10K ohm A .....	008-346-9-002
VR-402	Resistor, Variable,	RV-139 20K ohm B .....	008-346-9-003
VR-404,406	Resistor, Variable,	RV-289, DUAL; 10K ohm B/5K ohm B	008-346-9-004
VR-401	Resistor, Variable,	RV-126 100K ohm B .....	008-346-9-005
VR-403,S402	Resistor, Variable,	RV-008, 10K ohm A with SWITCH.....	008-299-9-001

**FIXED RESISTORS**

R-112	Resistor, Metal Film,	100 ohm 1W $\pm$ 10% .....	002-001-6-101
R-185	Resistor, Metal Film,	200 ohm 1W $\pm$ 10% .....	001-001-6-221
R-162	Resistor, Carbon Film,	22 ohm 1/2W $\pm$ 5% .....	002-102-5-220
R-305	Resistor, Carbon Film,	220 ohm 1/2W $\pm$ 5% .....	002-102-5-221
R-403	Resistor, Carbon Film,	1K ohm 1/2W $\pm$ 5% .....	002-102-5-102
R-423	Resistor, Carbon Film,	10K ohm 1/2W $\pm$ 5% .....	002-102-5-103
R-424	Resistor, Carbon Film,	2.2M ohm 1/2W $\pm$ 5% .....	002-102-5-225
R-150	Resistor, Carbon Film,	270 ohm 1/4W $\pm$ 5% .....	002-104-5-271

**CIRCUIT  
SYMBOL**

**DESCRIPTION**

**DYNASCAN  
PART NO.**

**FIXED RESISTORS (Continued)**

R-81	Resistor, Carbon Film, 100 ohm 1/8W	±5% .....	002-108-5-101
R-184	Resistor, Carbon Film, 150 ohm 1/8W	±5% .....	002-108-5-151
R-301,302	Resistor, Carbon Film, 330 ohm 1/8W	±5% .....	002-108-5-331
R-304	Resistor, Carbon Film, 470 ohm 1/8W	±5% .....	002-108-5-471
R-17,19,33,113,121,122, 303,421,422	Resistor, Carbon Film, 1K ohm 1/8W	±5% .....	002-108-5-102
R-47,49,146	Resistor, Carbon Film, 1.5K ohm 1/8W	±5% .....	002-108-5-152
R-419	Resistor, Carbon Film, 1.8K ohm 1/8W	±5% .....	002-108-5-182
R-416	Resistor, Carbon Film, 2.2K ohm 1/8W	±5% .....	002-108-5-222
R-417	Resistor, Carbon Film, 2.7K ohm 1/8W	±5% .....	002-108-5-272
R-415	Resistor, Carbon Film, 3.3K ohm 1/8W	±5% .....	002-108-5-332
R-115	Resistor, Carbon Film, 6.8K ohm 1/8W	±5% .....	002-108-5-682
R-52,57,86,180	Resistor, Carbon Film, 10K ohm 1/8W	±5% .....	002-108-5-103
R-27	Resistor, Carbon Film, 47K ohm 1/8W	±5% .....	002-108-5-472
R-67	Resistor, Carbon Film, 470K ohm 1/8W	±5% .....	002-108-5-474
R-55	Resistor, Carbon Film, 2.2 ohm 1/8W	±5% .....	002-108-5-229
R-153	Resistor, Carbon Film, 4.7 ohm 1/8W	±5% .....	002-108-5-479
R-163	Resistor, Carbon Film, 10 ohm 1/8W	±5% .....	002-108-5-100
R-8,21,61,119	Resistor, Carbon Film, 68 ohm 1/8W	±5% .....	002-108-5-680
R-23,42,43,46,83,127,149, 156,157,158,159	Resistor, Carbon Film, 100 ohm 1/8W	±5% .....	002-108-5-101
R-7,61	Resistor, Carbon Film, 150 ohm 1/8W	±5% .....	002-108-5-151
R-4,53,56,106,129,152	Resistor, Carbon Film, 220 ohm 1/8W	±5% .....	002-108-5-221
R-14,151,155,179,182	Resistor, Carbon Film, 330 ohm 1/8W	±5% .....	002-108-5-331
R-3,54	Resistor, Carbon Film, 470 ohm 1/8W	±5% .....	002-108-5-471
R-85,176,194	Resistor, Carbon Film, 560 ohm 1/8W	±5% .....	002-108-5-581
R-26,118,161	Resistor, Carbon Film, 680 ohm 1/8W	±5% .....	002-108-5-681
R-160	Resistor, Carbon Film, 820 ohm 1/8W	±5% .....	002-108-5-821
R-30,32,35,39,80,88,91, 93,107,114,126,128, 132,144,145,186	Resistor, Carbon Film, 1K ohm 1/8W	±5% .....	002-108-5-102
R-178	Resistor, Carbon Film, 1.2K ohm 1/8W	±5% .....	002-108-5-122
R-48,60,71,105,125	Resistor, Carbon Film, 1.5K ohm 1/8W	±5% .....	002-108-5-152
R-135,401,402,404,405, 406,407,408,409,410, 411,412,413	Resistor, Carbon Film, 1.8K ohm 1/8W	±5% .....	002-108-5-182
R-34,36,77,78,79,110, 131,154	Resistor, Carbon Film, 2.2K ohm 1/8W	±5% .....	002-108-5-222
R-6,72,192	Resistor, Carbon Film, 2.7K ohm 1/8W	±5% .....	002-108-5-272
R-2,16,18,25,31,50,58, 68,89,97,98,117,120, 124,189,199	Resistor, Carbon Film, 3.3K ohm 1/8W	±5% .....	002-108-5-332
R-38,177	Resistor, Carbon Film, 3.9K ohm 1/8W	±5% .....	002-108-5-392
R-20,37,111,123	Resistor, Carbon Film, 4.7K ohm 1/8W	±5% .....	002-108-5-472
R-136	Resistor, Carbon Film, 5.6K ohm 1/8W	±5% .....	002-108-5-562
R-75	Resistor, Carbon Film, 6.8K ohm 1/8W	±5% .....	002-108-5-682
R-141	Resistor, Carbon Film, 8.2K ohm 1/8W	±5% .....	002-108-5-822
R-11,12,13,15,29,40,44, 94,95,99,104,109,130, 133,134,137,140,143, 181,193	Resistor, Carbon Film, 10K ohm 1/8W	±5% .....	002-108-5-103
R-24,74	Resistor, Carbon Film, 12K ohm 1/8W	±5% .....	002-108-5-122
R-90,102	Resistor, Carbon Film, 15K ohm 1/8W	±5% .....	002-108-5-153
R-1,142	Resistor, Carbon Film, 18K ohm 1/8W	±5% .....	002-108-5-183
R-108,116,147,187,87	Resistor, Carbon Film, 22K ohm 1/8W	±5% .....	002-108-5-223

**CIRCUIT  
SYMBOL**

**DESCRIPTION**

**DYNASCAN  
PART NO.**

**FIXED RESISTORS (Continued)**

R-73,75,100	Resistor, Carbon Film, 33K ohm 1/8W	±5% .....	002-108-5-333
R-5,28,59,64,66,96,425	Resistor, Carbon Film, 47K ohm 1/8W	±5% .....	002-108-5-473
R-190	Resistor, Carbon Film, 68K ohm 1/8W	±5% .....	002-108-5-683
R-9,63,65,92,169,197,198	Resistor, Carbon Film, 100K ohm 1/8W	±5% .....	002-108-5-104
R-82	Resistor, Carbon Film, 150K ohm 1/8W	±5% .....	002-108-5-154
R-41,45	Resistor, Carbon Film, 180K ohm 1/8W	±5% .....	002-108-5-184
R-84	Resistor, Carbon Film, 270K ohm 1/8W	±5% .....	002-108-5-274
R-22	Resistor, Carbon Film, 330K ohm 1/8W	±5% .....	002-108-5-334
R-10	Resistor, Carbon Film, 470K ohm 1/8W	±5% .....	002-108-5-474
R-103	Resistor, Carbon Film, 1M ohm 1/8W	±5% .....	002-108-5-105
R-101	Resistor, Carbon Film, 1.8M ohm 1/8W	±5% .....	002-108-5-185

**CAPACITORS**

CT-1,2,3	Capacitor, Trimmer, 20pF	CV-028 .....	028-053-9-001
C-304	Capacitor, Electrolytic, 3300μF	35V CZ-046 .....	022-174-9-001
C-13,109	Capacitor, Tantalum, 0.1μF	25V ±20% .....	027-025-7-001
C-7,19	Capacitor, Tantalum, 0.22μF	16V ±20% .....	027-035-9-002
C-59,193	Capacitor, Tantalum, 1μF	25V ±20% .....	027-035-9-003
C-62,63	Capacitor, Tantalum, 2.2μF	25V ±20% .....	027-031-9-001
C-72	Capacitor, Tantalum, 4.7μF	10V ±20% .....	027-026-9-005
C-84,113	Capacitor, Tantalum, 22μF	6.3V ±20% .....	027-035-9-004
C-16,17,27,121,142,198	Capacitor, Electrolytic, 0.47μF	50V .....	022-157-9-001
C-119,146,162,169,183	Capacitor, Electrolytic, 1μF	50V .....	022-157-9-002
C-15,83	Capacitor, Electrolytic, 2.2μF	50V .....	022-158-9-002
C-73,102	Capacitor, Electrolytic, 4.7μF	25V .....	022-157-9-003
C-90,120,133	Capacitor, Electrolytic, 10μF	16V .....	022-157-9-004
C-117,164	Capacitor, Electrolytic, 10μF	25V .....	022-171-9-001
C-180	Capacitor, Electrolytic, 22μF	10V .....	022-163-9-001
C-24,26,92,114,191	Capacitor, Electrolytic, 47μF	10V .....	022-160-9-002
C-107	Capacitor, Electrolytic, 220μF	10V .....	022-171-9-002
C-302	Capacitor, Electrolytic, 220μF	16V .....	022-163-9-003
C-118	Capacitor, Electrolytic, 470μF	10V .....	022-160-9-001
C-66	Capacitor, Electrolytic, 1000μF	10V .....	022-171-9-003
C-134	Capacitor, Electrolytic, 1000μF	25V .....	022-171-9-004
C-58,115	Capacitor, Mylar, 0.001μF	50V ±10% .....	025-122-9-001
C-91	Capacitor, Mylar, 0.0022μF	50V ±10% .....	030-041-9-003
C-85,197	Capacitor, Mylar, 0.0047μF	50V ±10% .....	025-126-9-001
C-88,89,93,161,82	Capacitor, Mylar, 0.01μF	50V ±10% .....	025-121-9-002
C-55,108,111,25	Capacitor, Mylar, 0.022μF	50V ±10% .....	025-121-9-003
C-86,194	Capacitor, Mylar, 0.033μF	50V ±10% .....	025-121-9-004
C-301,303	Capacitor, Mylar, 0.039μF	50V ±10% .....	025-121-9-005
C-71,168,190	Capacitor, Mylar, 0.047μF	50V ±10% .....	025-121-9-006
C-28,61,79,110,116,150, 153	Capacitor, Mylar, 0.1μF	50V ±10% .....	025-121-9-001
C-53,185,186	Capacitor, Ceramic, 0.5pF	50V ±0.25pF	CH 020-209-9-001
C-139,147	Capacitor, Ceramic, 1pF	50V ±0.25pF	CH 020-180-9-001
C-160	Capacitor, Ceramic, 1.5pF	50V ±0.25pF	CH 020-204-9-001
C-38,42,44	Capacitor, Ceramic, 2pF	50V ±0.25pF	CH 020-180-9-002
C-22,23	Capacitor, Ceramic, 3pF	50V ±0.25pF	CH 020-180-9-003
C-36,80	Capacitor, Ceramic, 4pF	50V ±0.25pF	CH 020-190-9-031
C-21	Capacitor, Ceramic, 5pF	50V ±0.5pF	CH 020-204-9-003
C-65,105,126,132,140	Capacitor, Ceramic, 10pF	50V ±5%	CH 020-181-9-009
C-29	Capacitor, Ceramic, 12pF	50V ±5%	CH 020-190-9-033
C-79	Capacitor, Ceramic, 15pF	50V ±5%	CH 020-186-9-001

**CIRCUIT  
SYMBOL**

**DESCRIPTION**

**DYNASCAN  
PART NO.**

**CAPACITORS (Continued)**

C-64,104	Capacitor, Ceramic,	18pF	50V	±5%	CH .....	020-204-9-004
C-57	Capacitor, Ceramic,	27pF	50V	±5%	CH.....	020-104-9-005
C-43,175	Capacitor, Ceramic,	33pF	50V	±5%	CH .....	020-204-9-006
C-144	Capacitor, Ceramic,	39pF	50V	±5%	CH .....	020-204-9-009
C-69,70,158,195	Capacitor, Ceramic,	47pF	50V	±5%	CH .....	020-187-9-009
C-171	Capacitor, Ceramic,	56pF	50V	±5%	CH .....	020-192-9-001
C-8	Capacitor, Ceramic,	82pF	50V	±5%	CH .....	020-211-9-001
C-102,143	Capacitor, Ceramic,	100pF	50V	±5%	CH .....	020-190-9-034
C-10	Capacitor, Ceramic,	100pF	50V	±10%	RH .....	020-204-9-010
C-163	Capacitor, Ceramic,	120pF	50V	±10%	RH .....	020-181-9-006
C-145	Capacitor, Ceramic,	180pF	50V	±10%	RH .....	020-204-9-011
C-81	Capacitor, Ceramic,	270pF	50V	±10%	UJ.....	020-204-9-012
C-149,159,174	Capacitor, Ceramic,	330pF	50V	±10%	UJ.....	020-204-9-013
C-148	Capacitor, Ceramic,	390pF	50V	±10%	UJ.....	020-177-9-016
C-151	Capacitor, Ceramic,	470pF	50V	±10%	UJ.....	020-175-9-006
C-170	Capacitor, Ceramic,	100pF	50V	±10%	SL .....	020-180-9-016
C-127	Capacitor, Ceramic,	220pF	50V	±10%	SL.....	020-180-9-019
C-128	Capacitor, Ceramic,	470pF	50V	±10%	SL.....	020-205-9-009
C-3,6,9,30,31,32,34,39, 40,41,98,101,165,172, 192,403,404,405,406, 407,408,409,410,411, 415,416,417	Capacitor, Ceramic,	0.001μF	50V	±20%	YD .....	020-204-9-017
C-33,35,37,141,152,154, 155,156,157,173,184, 187,188,202,203,204, 401,402	Capacitor, Ceramic,	0.0047μF	50V	±20%	YD .....	020-204-9-018
C-48,60,67,74,75,77,78, 94,95,99,100,103,106, 122,123,124,125,129, 130,131,181,189,308, 310,412,413,196	Capacitor, Ceramic,	0.01μF	50V	±20%	YD .....	020-204-9-019
C-1,2,4,5,11,12,14,18,20, 45,46,47,49,50,51,52, 54,56,68,87,167,206, 208	Capacitor, Ceramic,	0.022μF	50V	+80% -20%	YF.....	020-204-9-020
C-421	Capacitor, Ceramic,	0.047μF	50V	+80% -20%	ZF.....	020-204-9-021
C-207,414	Capacitor, Ceramic,	0.1μF	50V	+80% -20%	ZF.....	020-204-9-022
CC-1	Capacitor Array,	HA-003	.....			527-077-9-002

**CRYSTALS**

X-1	Crystal QX-077,	10.24 MHz	.....	133-014-9-001
X-4	Crystal QX-094,	11.1125 MHz	.....	133-019-9-001
X-3	Crystal QX-083.	7.7975 MHz	.....	133-019-9-002
X-2	Crystal QX-084,	7.8025 MHz	.....	133-019-9-003

**MISCELLANEOUS**

Printed Circuit Board,	Main, PC-385AA	.....
Printed Circuit Board,	Channel Switch,	PC-395AA .....
Printed Circuit Board,	LED,	PC-396AA .....
Printed Circuit Board,	Power,	PC-006EB.....
Printed Circuit Board,	Mic Jack,	PC-389AA .....

CIRCUIT SYMBOL	DESCRIPTION	DYNASCAN PART NO.
<b>MISCELLANEOUS (Continued)</b>		
	Printed Circuit Board, PA EXT SP Jack, PC-401AA.....	
	Printed Circuit Board, Slide Switch, PC-402AA .....	
FT-1	Crystal Filter, FL-065 .....	143-008-9-001
FT-2	Crystal Filter, FL-046 .....	143-006-9-002
S-403	Rotary Switch, SR-205, Mode Switch.....	083-241-9-001
S-401	Rotary Switch, SR-209, Channel Switch .....	083-241-9-002
S-405-1,2	Slide Switch, SW-116, ANL/NB.....	084-065-9-001
S-408	Slide Switch, SW-116, SWR/CAL/MOD .....	084-065-9-001
S-404	Slide Switch, SW-117, PA/CB .....	084-065-9-002
S-409	Slide Switch, SW-099, AC/DC .....	084-065-9-003
SP-401	Speaker, SP-014 .....	580-025-9-001
M-401	Meter, MT-121, S/RF,PWR.....	320-097-9-001
M-402	Meter, MT-137, MOD,SWR.....	320-097-9-002
MIC	Microphone, MK-091.....	562-024-9-001
J-405	Connector, JK-068 Antenna .....	772-036-9-001
J-404	Jack, Microphone, JK-107 .....	773-092-9-001
J-403	Connector, JK-052, DC PWR.....	762-020-9-001
J-401,402	Jack, JK-010, PA/EXT SP .....	772-025-9-001
	Socket, Crystal, SK-023 .....	749-097-9-001
	Lug Terminal, TP-012 .....	757-042-9-001
TP-1,3,6,9,10	Terminal, Test Point, TP-019.....	757-029-9-002
TP-2,4,11	Terminal, Test Point, TP-020 .....	757-028-9-001
TP-7,8	Terminal, Test Point, TP-027 .....	757-032-9-002
	Fuse Holder, FH-002 .....	742-005-9-001
	Fuse FS-012, 4A .....	194-005-9-001
	Fuse FS-010, 4A .....	191-251-3-004
PL-401,402	Pilot Lamp, PL-068-012 14V/50mA .....	400-056-9-001
S-1	Insulation Plate, YD-003-002 .....	350-006-9-002
B-1	Insulation Bushing, YD-004-001 .....	350-006-9-001
	Insulation Plate, YD-040 .....	350-006-9-001
	Insulation Plate, YD-033 .....	345-050-9-002
	Insulation Plate, YY-027 .....	342-039-9-001
	Insulation Bushing, YY-036 .....	759-084-9-001
	Wire Clamper, YY-047 .....	380-278-9-001
	Insulation Plate, YD-039 .....	350-007-9-001
	Wire Clamper, YY-049 .....	380-284-9-002
	Wire Connector, YY-008 .....	763-083-9-001
	Wire Clamper, YY-023 .....	380-309-9-001
	Bushing, Snap-in, YY-024 .....	380-280-9-001
	Bushing, Snap-in, YY-025 .....	380-280-9-002
	DC Power Cord, W-070273 .....	426-042-9-001
	AC Power Cord, WZ-022 .....	420-027-9-001
	Chassis .....	257-106-9-001
	Rear Panel .....	262-021-9-001
	Cover, Top .....	253-057-9-001
	Cover, Bottom .....	252-022-9-001
	Switch Holder .....	251-206-9-001
	Panel Holder (R) .....	251-191-9-001
	Panel Holder (L) .....	251-208-9-001
	Heat Sink .....	747-064-9-001
	Heat Sink .....	747-054-9-002
	Pilot Lamp Holder.....	251-209-9-001
	Pilot Lamp Bracket .....	251-173-9-002
	Transformer Holder .....	251-229-9-001
	Microphone Hanger .....	741-074-9-001

**CIRCUIT  
SYMBOL**

**DESCRIPTION**

**DYNASCAN  
PART NO.**

**MISCELLANEOUS (Continued)**

Solder Lug .....	740-024-9-001
Front Panel .....	255-171-9-001
Knob .....	751-095-9-002
Knob .....	751-152-9-001
Knob .....	751-147-9-002
Channel Knob .....	751-147-9-003
Control Nameplate .....	260-161-9-001
Brand Nameplate .....	260-161-9-002
FCC Nameplate .....	
Serial Number Label .....	
Warning Label .....	
Caution Label .....	
Caution Label .....	
Fuse Replacement Label .....	
Production Date Label .....	
Light Shield Plate, LED .....	763-085-9-003
Rubber Washer .....	347-075-9-001
Speaker Net .....	763-085-9-004
Rubber Washer .....	347-072-9-001
Protection Cover .....	343-024-9-001
Protection Cover .....	343-024-9-002
Wool Coated Paper .....	769-086-9-001
Wool Coated Paper .....	769-096-9-001
Wool Coated Paper .....	769-096-9-002
Meter Cushion .....	769-096-9-003
Protection Pad .....	343-024-9-005
Protection Pad .....	503-136-9-001
Rubber Cap for LED .....	753-008-9-002
Lug Terminal .....	345-052-9-001
Cord Stopper .....	763-111-9-002
Vinyl Bag, Misc. ....	
Vinyl Bag, Mic. ....	
Vinyl Bag, DC Cord .....	
Vinyl Bag, Printed Matters .....	
Vinyl Bag, Fuse .....	
Rubber Foot .....	381-079-9-001
Spring for Knob .....	763-084-9-004
Spring for Knob .....	763-085-9-005
Ribet .....	733-022-9-001
Polystyrol Foam .....	503-130-9-001
Polystyrol Foam .....	503-130-9-002
Protection Pad .....	343-024-9-004
Accessory Box .....	500-324-9-001
Shipping Carton Box .....	500-373-9-001
Display Box .....	500-374-9-001
Screw, Pan Head, 3D x 6, Metric .....	634-051-9-001
Screw, Bind Head, 2D x 4, Metric .....	634-069-9-002
Screw, Bind Head, 2.6D x 4, Metric .....	634-073-9-001
Screw, Bind Head, 2.6D x 6, Metric .....	634-099-9-002
Screw, Bind Head, 2.6D x 10, Metric .....	634-088-9-004
Screw, Bind Head, 3D x 6, Metric .....	634-053-9-001
Screw, Bind Head, 3D x 12, Metric .....	634-103-9-001
Screw, Bind Head, 4D x 10, Metric .....	634-084-9-001
Screw, Bind Head, 5D x 10, Metric .....	634-077-9-002
Tapping Screw, 3D x 8, Metric .....	710-037-9-002



CIRCUIT  
SYMBOL

DESCRIPTION

DYNASCAN  
PART NO.

MISCELLANEOUS (Continued)

Tapping Screw,	3D x 8, Metric .....	710-032-9-002
Tapping Screw,	3D x 10, Metric .....	710-019-9-001
Tapping Screw,	3.5D x 8, Metric.....	710-020-9-001
Tapping Screw,	3D x 6, Metric .....	710-021-9-003
Tapping Screw,	3D x 12, Metric .....	710-037-9-001
Tapping Screw,	3D x 14, Metric .....	710-032-9-001
Hex Nut,	2.6D, Metric .....	653-030-9-001
Hex Nut,	3D, Metric .....	634-024-9-001
Flange Nut,	4D, Metric .....	653-037-9-001
Washer,	3ID, Metric .....	724-021-9-001
Spring Washer,	2.6ID, Metric .....	731-049-9-002
Spring Washer,	3ID, Metric .....	731-050-9-001
Lock Washer,	3.5ID, Metric .....	731-041-9-001
Spring Nut,	3ID, Metric .....	653-024-9-002
Spring for Knob .....		763-084-9-003
Owner's Manual .....		480-233-9-001
Circuit Diagram/Bill of Material .....		499-139-9-001
FCC Application Form .....		
Warranty Card .....		
Service Station Card .....		
FCC Temporary Licence Form.....		
FCC Part 95 Rules .....		