

This Information Is Provided By
CBTricks.com

Realistic 21-1172 Microphone

Liability of damages to any equipment is the sole responsibility of the user! Downloading, viewing, or using any information provided on these pages automatically accepts the user to the terms of this agreement!

Modifications are provided for information purposes only!

Supporters of CBTricks.com paid for the hosting so you would have this file.

CBTricks.com is a non-commercial personal website was created to help promote the exchange of service, modification, technically oriented information, and historical information aimed at the Citizens Band, GMRS (CB "A" Band), MURS, Amateur Radios and RF Amps.

CBTricks.com is not sponsored by or connected to any Retailer, Radio, Antenna Manufacturer or Amp Manufacturer, or affiliated with any site links shown in the links database. The use of product or company names on my web site is not endorsement of that product or company.

The site is supported with donations from users, friends and selling of the Site Supporters DVD's to cover some of the costs of having this website on the Internet instead of relying on banner ads, pop-up ads, commercial links, etc. Thus I do not accept advertising banners or pop-up/pop-under advertising or other marketing/sales links or gimmicks on my website.

ALL the money from donations is used for CBTricks.com I didn't do all the work to make money (I have a day job). This work was not done for someone else to make money also, for example the ebay CD sellers.

All Trademarks, Logos, and Brand Names are the property of their respective owners.

This information is not provided by, or affiliated in any way with any radio or antenna Manufacturers.

Thank you for any support you can give.


For information on how to Support CBTricks.com

<http://www.cbtricks.com/support/>

REALISTIC®

HAND HELD DYNAMIC MICROPHONE


Catalog Number: 21-1172



SPECIFICATIONS

Type : Dynamic, hand held, with push-to-talk switch
 Impedance : 600 ohms
 Output : -70 dB at 1 kHz (0 dB = 1 V/ μ bar);
 = 0.25 millivolts
 Frequency : 300-7,000 Hz
 Directivity : Omni-directional
 Cable : Coiled cord, terminated with 5-pin DIN plug
 Accessories: Clip-hanger ... 1
 Screw ... 2

SCHEMATIC DIAGRAM



Function/Operation of Mic Connector Pins

Pin Number	Button Out (Receive)	Button In (Transmit)
1	Shield/Ground	Shield/Ground
2	Connected to Pin 4	Floating free
3	Floating free	Grounded to Pin 1
4	Connected to Pin 2	Audio "hot"
5	Grounded to Pin 1	Floating free