

TRISTAR 747

CLARIFIER MODIFICATION

for Slide see Vol 17 Pg. 35

1. Clip D6, D7.
2. Run Brown wire to cathode D6 from clarifier.
3. Hook wire from unused terminal on clarifier to stable 9Vdc source.
4. Remove C14.
5. Install 2-30pf variable cap from crystal to ground.
(Install it to side of crystal closest to front of radio)
6. Tune for Max. freq. with clarifier fully CW. Should get +5 -2½ KC slide.

