

SPECIFIC TUNE-UPS

Gemtronics GTX-3323: VR152 - AGC; VR151 - S Mtr.; VR491 - RF Mtr.;
VR181 - Sq. Rng.; VR481 - AMC (Don't defeat)
TX - I431, I432, I433, I441, I451, I463, I464
RX - L111, L112, L121, L122, L131, L141, L151

Midland 102M (77-102)

RV102 - S Meter; RV202 - RF Meter; RV101 - Sq. Range; The other
unmarked pot is for AMC adjustment. (Do not defeat)....

PLL CHIPS

Following is list of identical pin-outs for chips — this is
not to say that all will modify the same way or PLL logic B+'s are
also:

MB8719, MB8734

MC145104, MM55104, MN6040A, SM5104, 00S09

MC145106, MM55106, MM55116, MM55126

MC145107, MM55107, SM5107

MM55108, SM5118

MC145109, PLL02A, PLL02AG, SM5109, TC9100P

uPD2814C, HD42853, KM5624, uPD2824C

Manufacturers I.D. for prefix's:

HD - Hitachi

LC - Sanyo

M - Mitsubishi

MB - Fujitsu

MC - Motorola

MM - National Semiconductor

MN - Panasonic

MSM - OKI Semiconductor

NIS - Seiko

TC - Toshiba

uPD - Nippon Elec. Corp.

...any additional contributions would be appreciated..
T.U.