

TRAM DIAMOND 60
15KC SLIDER

- (1) Remove the unit from its cabinet and locate the three points shown.
- (2) Solder the points together with a small piece of wire as also shown.
- (3) Adjust the 500r Resistor in the counter clockwise direction until the bottom range desired is reached.
- (4) If the range is not desired or will not drop as far as desired, L301, located just to the left of the three pots, can be adjusted clockwise to increase the down range.

