

SPECIFIC RADIO TUNE-UPS (Cont'd):

PACE 8003:

RX: VR109; IF AGC  
VR101; RF AGC  
VR102; SQ Range  
VR103: S Meter

TX: Peak T503, T504, T302, L303, CT301, L304  
VR201; AMC (disable C219)  
VR301; RF Meter

PACE 8016:

RX: R114; Squelch range  
R107; Meter zero  
R108; S meter adjust

TX: Peak; L115, L114, L112, L109, L106  
R168; AMC (defeat C178)  
Pour it to this one - it has a 25 Watt Final!

PACE 8117:

RX R135; SQ Range  
R137; S Meter

TX: Peak L301, T301, L302, T302, L304, L307, L308  
R220; AMC (defeat CR201)  
R325; RF Meter

PANASONIC RJ-3250:

Change '90 day wonder' on final.  
Audio Board - remove R70 (variable 100K resistor) AMC control  
defeat.

RX: R24; Squelch range  
R22; S meter adjust  
R105; VU/Mod meter adjust

TX: Tune; L8 & L16 for maximum modulation  
Peak; T11, T12, T13, T14, T15, FL1, L18  
R73; RF meter adjust

NOTE: Do not exceed 6 watts dead key!