

SPECIFIC RADIO TUNE-UPS (Cont'd):

Sharp CB-4470:

RX: R43; SQ. Range

TX: Peak T301, T302, T303, T304, L302, L301.
R110; AMC
T202; VCO Coil.

Install Zapper @ C210 for extra frequencies.

Teaberry Stalker IV TC9109P:

RX: VR7; If Gain.
VR3; Squelch Range.
VR4; S Meter.

TX: Adjust L10, L11, L12, L15 for Max. L18 is T.V.I. Filter
VR6; AMC or remove TR8
VR5; Power Meter.
L9; VCO Coil.

TRS Challenger 1200:

RX: VR2; AGC
VR5; SQ. Range
VR3; S Meter

TX: Peak T214, L204, CV101, L205.
VR6; AM Power
VR1; AMC or clip D201.
VR4; RF Power Meter.

Install Zapper @ C111 for extra frequencies.